

Model. WCS12B

Switch 10Amp 1 Gang 2 Way



Features & Benefits

- Fits (minimum) box depth 16mm
- Terminal capacity 3x1.5mm² (10Amp AX rating only)
- Front plate depth 10mm (for single & double)
- Supplied with 2 x 30mm M3.5 screws

Safety Information

IMPORTANT - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
- Do not dispose of decommissioned fitting in household waste
- Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

Technical Specifications

| General Information | |
|--------------------------------------|----------------------|
| Colour/Finish | Chrome |
| Dimensions (mm) | 95 x 95 x 10mm |
| Front Plate Depth (mm) | 8mm |
| Fixing Centre (mm) | 60.3mm |
| Minimum Box Depth (mm) | 16mm |
| Electrical | |
| Rated Operating Voltage (v) | 240v |
| Terminal Capacity (mm ²) | 3x1.5mm ² |
| Number Earth Terminals | 1 |
| Rated Load Capacity (Amps) | 13A 10AX |
| Frequency (Hz) | 50/60Hz |
| Approvals | BS3676 |
| Kite Mark / ASTA | KM73110 |
| Performance Data | |
| Switch (1 / 2) etc | 1 Switch |
| Control (1 / 2 Way) | 2 Way |
| Lugs | 2 |
| Construction | |
| Body | Steel plated brass |
| Insert Colour | Black |
| Warranty (Years) | 25 |
| Other | |