

Model. GTLED16MS

2D 16W LED Microwave Motion Sensor Gear Tray

Features & Benefits

- LED 2D 16W SMD Gear Tray
- To fit any fitting already installed
- Microwave motion sensor

Safety Information

IMPORTANT - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
- Do not dispose of decommissioned fitting in household waste
- Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

Technical Specifications

General Information	
Product Colour/Finish	White
Dimensions (mm)	Ø263
Electrical	
Input Voltage (V)	230 - 240V
Frequency (Hz)	50/60Hz
Wattage (W)	16W
Wattage Equivalent (W)	2D 28W
Dimmable (Y/N)	N
Approvals	CE, TUV, GS
Class	I
Performance Data	
Useful Lumen Output	1700Lm
Lumens (Per Watt)	106Lm
Power Factor	>0.9
Average Lifespan (Hours)	35,000Hrs
CRI: Ra	>80
Colour Temperature (K)	65000K
Beam Angle (°)	n/a
LED Type	SMD 5630
Number of LED (pcs)	36 PCS
Energy Rating (ErP)	A
Sensor	
Sensor Interval (mins)	10sec - 30mins
Sensor Range (Mtrs / °)	1-10mtrs adjustable
Emergency	
Emergency Output (W)	n/a
Emergency Period (Hours)	n/a
Construction	
Body Material	Polycarbonate
Diffuser Material	Opal Diffuser
Weight	0.75Kg
Warranty Period (Years)	2Yrs
Other	
Applications	SMD Gear Tray for existing fittings

LIGHTING DESIGN

IMPORTANT!

We now offer a full lighting design service exclusively to all our customers

COMPLETELY FREE