

## Model. RCD63BR

Double Pole RCD for Consumer Units - 63A, 30mA



### Features & Benefits

- Provides earth fault safety protection and prevent fatal electric shock on a person
- Protect plant & machinery from fire by a current passing from live to earth that a fuse or circuit break may not detect
- Tunnel terminal type

### Safety Information

**IMPORTANT** - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
- Do not dispose of decommissioned fitting in household waste
- Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

### Technical Specifications

<b>General Information</b>	
Product Colour/Finish	Grey
<b>Electrical</b>	
Rated Voltage	230 - 240V
Frequency (Hz)	50/60Hz
Sensitivity	30mA
Terminal Capacity (mm <sup>2</sup> )	Up to 35mm <sup>2</sup>
<b>Performance Data</b>	
Specifications	BSEN61008-1
AMPS	63Amp
Poles	Double Poles
Type	AC
Breaking Capacity	6kA
Approvals	RoHS, CE
<b>Construction</b>	
Weight	0.211Kg
Warranty Years	1Yr
Body Material	Acrylic
<b>Others</b>	
Applications	Domestic and commercial applications