





13Amp 3 Pin RCD Adaptor 30mS-30mA

Features & Benefits

- 30mA Sensitivity
- Trip Time 40ms

Safety Information

IMPORTANT - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
 Do not dispose of decommissioned fitting in household waste
 Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

Technical Specifications

| General Information | |
|-----------------------------|--|
| Colour/Finish | White |
| Dimensions (mm) | 110X70X55 |
| Ingress Protection (IP) | IP20 |
| Electrical | |
| Rated Operating Voltage (v) | 220-240 |
| Rated Load Capacity (Amps) | 13 |
| Frequency (Hz) | 50/60 |
| Number Poles | 2 |
| Approvals | BS 7091/CE |
| Maximum Load | 13A |
| Performance Data | |
| Outlets (1 / 2) etc | 1 |
| Switch (1 / 2) etc | 2 Test and Reset |
| Construction | |
| Body | ABS |
| Warranty (Years) | 1 |
| Other | |
| Applications | Lawnmowers, Hedge Trimmers, Drills etc |

