

Model. WCS20NB

Switch 20Amp Double Pole (Neon)



Features & Benefits

There are currently no features entered for this product item.

Safety Information

IMPORTANT - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
- Do not dispose of decommissioned fitting in household waste
- Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

Technical Specifications

| General Information | |
|-----------------------------|----------------|
| Colour/Finish | Chrome |
| Dimensions (mm) | 95 x 95 x 10mm |
| Front Plate Depth (mm) | 8mm |
| Fixing Centre (mm) | 60.3mm |
| Minimum Box Depth (mm) | 25mm |
| Electrical | |
| Rated Operating Voltage (v) | 240v |
| Rated Load Capacity (Amps) | 20A |
| Frequency (Hz) | 50/60Hz |
| Number Poles | 2 |
| Approvals | BS3676 BSEN |
| Kite Mark / ASTA | KM73109 |
| Performance Data | |
| Switch (1 / 2) etc | 1 Switch |
| Construction | |
| Insert Colour | Black |
| Warranty (Years) | 25 |
| Other | |