

No Image

## Model. WSCSPS

Fused Switched Spur 13Amp

### Features & Benefits

There are currently no features entered for this product item.

### Safety Information

**IMPORTANT** - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
- Do not dispose of decommissioned fitting in household waste
- Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

### Technical Specifications

| General Information                  |  |
|--------------------------------------|--|
| Colour/Finish                        | Satin chrome                           |
| Dimensions (mm)                      | 95 x 95 x 10mm                         |
| Front Plate Depth (mm)               | 8mm                                    |
| Fixing Centre (mm)                   | 60.3mm                                 |
| Minimum Box Depth (mm)               | 25mm                                   |
| Electrical                           |  |
| Rated Operating Voltage (v)          | 240v                                   |
| Terminal Capacity (mm <sup>2</sup> ) | 2.5mm <sup>2</sup>                     |
| Rated Load Capacity (Amps)           | 13A                                    |
| Frequency (Hz)                       | 50/60Hz                                |
| Approvals                            | BS1363                                 |
| Kite Mark / ASTA                     | KM73110                                |
| Performance Data                     |  |
| Switch (1 / 2) etc                   | 1 Gang                                 |
| Construction                         |  |
| Body                                 | Steel coated brass with chrome plating |
| Insert Colour                        | White                                  |
| Warranty (Years)                     | 25                                     |
| Other                                |  |