





Model. CEDS11

Switch 1 Gang 1 Way 10Amp

Features & Benefits

There are currently no features entered for this product item.

Safety Information

IMPORTANT - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
 Do not dispose of decommissioned fitting in household waste
 Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

Technical Specifications

| General Information | |
|--------------------------------------|--------------------|
| Colour/Finish | White |
| Dimensions (mm) | 86 x 86 x 9mm |
| Front Plate Depth (mm) | 9mm |
| Fixing Centre (mm) | 60.3mm |
| Minimum Box Depth (mm) | 16mm |
| Electrical | |
| Terminal Capacity (mm ²) | 2.5mm ² |
| Rated Load Capacity (Amps) | 10A |
| Approvals | BS3676-BSEN 60669 |
| Kite Mark / ASTA | KM73110 |
| Performance Data | |
| Outlets (1 / 2) etc | 1 Gang |
| Construction | |
| Body | Urea Formaldehyde |
| Warranty (Years) | 25 |
| Other | |

