MERIDIAN





Model. FLC2BC

2W Filament Candle Lamp 3000K

Features & Benefits

There are currently no features entered for this product item.

Safety Information

IMPORTANT - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
- Do not dispose of decommissioned fitting in household waste
- Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

Technical Specifications

| General Information | |
|--------------------------|--------------------------------------|
| Product Colour/Finish | Clear |
| Dimensions (mm) | Ø35x90 |
| Electrical | |
| Input Voltage (v) | 220-240V |
| Frequency (Hz) | 50/60Hz |
| Wattage (W) | 2W |
| Wattage Equivalent (W) | 25W |
| Dimmable (Y/N) | N |
| Approvals/Certifications | CE / ERP |
| Performance Data | |
| Useful Lumen Output | 230 |
| Lumens (Per Watt) | 115 |
| Power Factor | >0.5 |
| Average Lifespan (Hours) | 25,000 |
| CRI: Ra | >80 |
| Colour Temperature (K) | 3000 |
| Beam Angle (°) | 320° |
| LED Type | Filament LED |
| Number of LED (pcs) | 1 |
| Energy Rating (ErP) | A++ |
| Sensor | |
| Emergency | |
| Construction | |
| Body Material | Glass |
| Diffuser Material | Clear |
| Weight (g) | 0.028 |
| Warranty Period (Years) | 1 |
| Other | |
| Applications | Domestic and commercial applications |
| | |

LIGHTING DESIGN

IMPORTANT!

We now offer a full lighting design service exclusively to all our customers

COMPLETELY FREE



