



Model. FLGB4SBC

4W Filament Candle Lamp 3000K

Features & Benefits

• 240V LED Filament globe

Safety Information

IMPORTANT - Before undertaking any work on or maintenance of fitting:-

- Switch off power supply and allow sufficient time to cool before handling
- Do not dispose of decommissioned fitting in household waste
- Dispose of fitting in the appropriate section of your local civic amenity site or recycling centre only

Technical Specifications

| l'échinical opéénicatione | |
|---------------------------|--------------|
| General Information | |
| Product Colour/Finish | Clear |
| Dimensions (mm) | 45x78 |
| Electrical | |
| Input Voltage (V) | 220-240V |
| Frequency (Hz) | 50/60Hz |
| Wattage (W) | 4W |
| Wattage Equivalent (W) | 40W |
| Dimmable (Y/N) | Ν |
| Approvals | CE / ERP |
| Performance Data | |
| Useful Lumen Output | 460 |
| Lumens (Per Watt) | 115 |
| Power Factor | >0.5 |
| Average Lifespan (Hours) | 25,000 |
| CRI: Ra | >80 |
| Colour Temperature (K) | 3000 |
| Beam Angle (°) | 320° |
| LED Type | Filament LED |
| Number of LED (pcs) | 1 |
| Energy Rating (ErP) | A++ |
| Sensor | |
| Emergency | |
| Construction | |
| Body Material | Glass |
| Diffuser Material | Clear |
| Weight | 0.034 |
| Warranty Period (Years) | 2 |
| Other | |
| | |

LIGHTING DESIGN

IMPORTANT!

We now offer a full lighting design service exclusively to all our customers

COMPLETELY FREE



